


LED Dimmer Switch ELD61

NEW

ELD61/12-36V DC



B14



Power MOSFET for LED lamps 12-36V DC up to 4A, pulse width modulation PWM. Stand-by loss 0.1 Watt only. With adjustable minimum brightness or dimming speed. With switching operation for children's rooms and snooze function

For installation. 45 mm long, 55 mm wide, 18 mm deep.

Dimmer switch for R- and LED loads up to 4 A depending on ventilation conditions.

Zero passage switching with soft start and soft OFF to protect lamps.

Control voltage input 12 to 36V DC, depending on the connected LED illumination.

A pulse resistant switching power supply unit is necessary.

Universal control voltage 8..230V UC, electrically isolated from the supply voltage.

Either direction pushbuttons can be connected to ▲ ▼ or these terminals will be bridged and a pushbutton will be connected as an universal pushbutton.

With universal pushbutton: short commands switch on/off, permanent control changes the brightness to the maximum. An interruption of the control changes the dimming direction.

With direction pushbutton: switching and dimming on with ▲, turning and dimming off with ▼ A dual pulse with ▲ effects dimming on up to the maximum brightness with the set dimming speed (dimspeed).

The set brightness level will be stored when turning off (Memory).

In case of power failure the switching position and the brightness level will be stored and will be switched on when supply voltage recurs.

Automatic electronic overload protection and overtemperature switch off.


With the top rotary switch % ⚙️ / dim speed either the minimum brightness level (completely dimmed down) or the dim speed can be adjusted.

The lower rotary switch determines the load type to which the dimming curve is set: position 1 is the standard setting. With position 2 and 3 it can be varied on request.

With switching operation for children's rooms (universal or direction pushbutton ▲): if the light is switched on by holding down the pushbutton it starts at the lowest brightness level after approx. 1 second and dims up slowly as long as the pushbutton is pressed without modifying the latest stored brightness level.

Snooze function (universal or direction pushbutton ▼): with a double impulse the lighting is dimmed down from the current dimming position to the minimum brightness level and switched off. The current dimming position as well as the adjustable minimum brightness level determine the dimming time (max. = 60 minutes) which can be reduced as required. It can be switched off at any time by short-time control commands during the lighting is dimmed down. Holding down the pushbutton during the dimming down process dims up and stops the snooze function.

Function rotary switches



Standard setting ex factory.

Typical connection

